




Dimensions



Accessories



LARK

|           |                       |
|-----------|-----------------------|
| Name      | ORBITAL MINI 2 LARK W |
| Reference | A1962100W             |
| Color     | Matt white            |
| RAL       | 9016                  |
| Category  | CEILING RECESSED      |

|              |                 |
|--------------|-----------------|
| Type         | LARK   EXCL     |
| Power        | Max 2 X 7,5 W   |
| LED lifespan | L80B10 >60.000h |

|                             |                                  |
|-----------------------------|----------------------------------|
| Driver                      | Excluded                         |
| Dimming                     | No Dim / DALI / Push / Phase Cut |
| Electrical insulation class | <input type="checkbox"/>         |

|                        |                    |
|------------------------|--------------------|
| Sealing                | IP20               |
| Wireless control       | Please Consult     |
| Emergency power supply | Please Consult     |
| Recess measurements    | 113 x 204 mm       |
| Swivel angle           | X30° Y30°          |
| Weight                 | 1030 g             |
| Packaged weight        | 1195 g             |
| Packaging dimensions   | 251 x 154 x 154 mm |
| Units per package      | 1                  |
| Materials              | Aluminium          |

PRODUCT

LIGHT SOURCE

LIGHTING FIXTURE | ELECTRICAL DATA

OTHER DATA



Orbital Mini is a ceiling recessed luminaire whose beam can be directed in an angle of up to 30 degrees per axis. Versatile, functional and -due to its small size- very discrete and elegant.



| Lark                                                                                                 |            | P    | CCT   | I     | Flux    | Flux Out | LOR |
|------------------------------------------------------------------------------------------------------|------------|------|-------|-------|---------|----------|-----|
|                                                                                                      | 0434-00-96 | 5W   | 2700K | 140mA | 700 lm  | 644 lm   | 92% |
|                                                                                                      | 0434-00-05 | 5W   | 3000K | 140mA | 730 lm  | 672 lm   | 92% |
|                                                                                                      | 0434-00-19 | 5W   | 4000K | 140mA | 750 lm  | 690 lm   | 92% |
| <br>PHASE CUT *   | 0434-01-02 | 7,5W | 2700K | 200mA | 950 lm  | 874 lm   | 92% |
|                                                                                                      | 0434-00-09 | 7,5W | 3000K | 200mA | 1000 lm | 920 lm   | 92% |
|                                                                                                      | 0434-00-17 | 7,5W | 4000K | 200mA | 1030 lm | 948 lm   | 92% |
|                                                                                                      | 0434-01-03 | 7,5W | 2700K | 200mA | 950 lm  | 874 lm   | 92% |
|                                                                                                      | 0434-00-15 | 7,5W | 3000K | 200mA | 1000 lm | 920 lm   | 92% |
|                                                                                                      | 0434-00-18 | 7,5W | 4000K | 200mA | 1030 lm | 948 lm   | 92% |
| <br>DALI   PUSH * | 0434-01-04 | 7,5W | 2700K | 200mA | 950 lm  | 874 lm   | 92% |
|                                                                                                      | 0434-01-05 | 7,5W | 3000K | 200mA | 1000 lm | 920 lm   | 92% |
|                                                                                                      | 0434-01-06 | 7,5W | 4000K | 200mA | 1030 lm | 948 lm   | 92% |

220  
240

V~

CRI>80

L90B10  
>55.000h


MacAdam  
Step 2

INCL

FAST | CONNEC

38°

\* OTHER DIM OPTIONS PLEASE CONSULT



Fuente de luz (LED) reemplazable por un profesional autorizado

Replaceable (LED only) light source by an authorized professional.

Source lumineuse (LED) remplaçable par un professionnel agréé

Sorgente luminosa (LED) sostituibile da parte di un professionista autorizzato

Austauschbare (LED) Lichtquelle durch einen autorisierten Fachmann



Equipo de control reemplazable por un profesional autorizado

Replaceable control gear by an authorized professional

Dispositif de commande remplaçable par un professionnel agréé

Alimentatore sostituibile da parte di un professionista autorizzato

Auswechselbares Betriebsgerät durch autorisierten Fachmann

## Instrucciones para el final de vida y la eliminación de los componentes:

### Instructions on end-of-life and component disposal:


### Instructions pour la gestion des composants en fin de vie et leur mise au rebut :

### Istruzioni per il fine vita e lo smaltimento dei componenti:


### Anweisungen zur entsorgung der Leuchtenkomponenten:



Interrumpir la alimentación del aparato  
Cut the power supply to the luminaire  
Couper l'alimentation du luminaire  
Interrompere l'alimentazione dell'apparecchio  
Stromversorgung der Leuchte unterbrechen



Quitar la(s) fuente(s) de luz para el desecho  
Remove light source(s) for disposal  
Retirer la (les) source(s) lumineuse(s) pour l'élimination  
Rimuovere la/le sorgente/e di luce per lo smaltimento  
Lichtquelle(n) zur Entsorgung entfernen



Quitar la batería para el desecho  
Remove the battery for decommissioning  
Retirer la batterie pour sa mise au rebut  
Rimuovere la batteria per la dismissione  
Die Batterie ordnungsgemäß entsorgen



Quitar el equipo de control para el desecho  
Remove control gear for disposal  
Retirer le dispositif de commande pour l'élimination  
Rimuovere l'alimentatore per lo smaltimento  
Betriebsgerät zur Entsorgung ausbauen

Enviar los materiales a un centro de recogida RAEE  
Send the materials to a WEEE collection centre  
Envoyer les matériaux dans une déchetterie DEEE  
Inviare i materiali ad un centro di raccolta RAEE  
Die Materialien in einem WEEE-Zentrum entsorgen

